

表 21-6 S Mode-1 PW1235 PAR(2)

接口名称	VGA					TV / AV / YCbCr					
信号格式	VGA @60	VGA @75	SVGA @60	SVGA @75	XGA @60	480i			576i		
参数项目	Nor	Nor	Nor	Nor	Nor	Nor	16:9	Exp	Nor	16:9	Exp
PW Mem-58	80	80	80	80	80	80	80	80	80	80	80
PW Mem-59	00	00	00	00	00	00	06	0B	00	06	0D
PW Mem-5C	D3	D0	E5	E5	FE	59	D9	D9	59	D9	D9
PW Mem-5D	78	78	82	82	82	77	77	62	77	87	85
PW DISP-62	80	45	90	8A	6A	80	80	80	7D	7D	7D
PW DISP-63	6A	A4	7A	80	D2	80	80	80	72	72	72
PW DISP-67	02	02	02	02	02	02	02	02	03	03	03
PW DISP-68	22	22	22	22	22	0D	6A	0D	0D	62	0D
PW DISP-72	73	6F	88	86	9B	B0	B0	B0	B3	B3	B3
PW DISP-73	82	82	82	82	82	86	66	87	86	5E	98
Pr-480P	80	80	80	80	80	80	80	80	80	80	80
Pb-480P	80	80	80	80	80	80	80	80	80	80	80
Pr-720P	80	80	80	80	80	80	80	80	80	80	80
Pb-720P	80	80	80	80	80	80	80	80	80	80	80
Pr-1080i	80	80	80	80	80	80	80	80	80	80	80
Pb-1080i	80	80	80	80	80	80	80	80	80	80	80

注:OSD 根据输入信号源和图像模式,每次只出现上述 S Mode-1 两表中相应格式所
在列的参数值。

表 21-7 S Mode-2-S Mode-9

S Mode-2 W / BPIP PAR

S Mode-3 Tda 9178(1)

Drive-R	31	AMS	0
Drive-G	31	LDH	1
Drive-B	31	CFS	1
Cutoff-R	07	FHS	1
Cutoff-G	07	WLB	0
Cathode *	0A	VDC	1
PWL *	0A	DEM	0
Scr Volt	OK	CD	04
PIP HPOS-L *	11	OSP	0
PIP VPOS-L *	1B	WPO	0
PIP HPOS-R *	41	DSK	1
PIP VPOS-R *	1B	ASK	1
PIP NR *	01	WSK	0
PIP YC-DLY *	00	SSK	0
FAV HPOS	2A	DGR	1
FAV VPOS	2A	GGR	0