

S Mode-0 TDA9332 HV

	TV/AV/ YCbCr(576i)	YPbPr (576P)	YPbPr (720P@50Hz)	YPbPr (1080i@50Hz)	VGA (VGA@60Hz)
V-Wait *	1A	1A	1A	1A	1A
V-Slope	2D	28	2A	2D	2B
V-Amp	1F	26	24	23	22
V-Shift	24	25	25	24	28
V-Zoom *	19	19	19	19	19
V-Scroll	1F	1F	1F	1F	1F
V-Cor	12	08	0D	10	0C
H-Shift	17	16	16	0E	0D
H-PARA	07	07	07	07	07
H-BOW	07	08	08	08	07
EW-Width	3A	3B	3A	37	3D
EW-PARA	0E	0D	0C	0C	0C
EW-Hcorn	26	1D	18	1D	13
EW-Lcorn	2D	2B	24	23	21
EW-Trap	1D	1C	1D	1E	1A
EW-EHT	19	19	19	19	19

注: OSD 显示根据实际输入信号源, 每次只出现上述两表中 S Mode-0 相应格式所在列的参数值。

S Mode-1 PW1235 PAR

接口名称	VGA									
制式系统	VGA@60		VGA@75		SVGA@60		SVGA@75		XGA@60	
参数项目	Nor	4:3	Nor	4:3	Nor	4:3	Nor	4:3	Nor	4:3
PW Mem-58	80	80	80	80	80	80	80	80	80	80
PW Mem-59	00	00	00	00	00	00	00	00	00	00
PW Mem-5C	D3	D3	D0	D0	E5	E5	E5	E5	FE	FE
PW Mem-5D	78	78	7D	7D	82	81	82	82	82	82
PW DISP-62	80	90	45	7C	90	AE	8A	8E	6A	F4
PW DISP-63	6A	C5	A4	E6	7A	D1	80	FF	D2	A0
PW DISP-67	02	02	02	02	02	02	02	02	02	02
PW DISP-68	22	22	22	22	22	22	22	22	22	22
PW DISP-72	73	54	6F	4F	88	65	86	65	9B	82
PW DISP-73	82	83	89	89	82	82	82	82	82	82
P _T / Pb-480P	80	80	80	80	80	80	80	80	80	80
P _T / Pb-720P	80	80	80	80	80	80	80	80	80	80
P _T / Pb-1080i	80	80	80	80	80		80	80	80	80

注: 注: OSD 显示根据实际输入信号源和图像压缩模式, 每次只出现上述三表中 S Mode-1 相应格式所在列的参数值。