

更多彩电维修资料请到《彩电维修资料网》<http://www.tv160.com> 查询!

机芯	代表机型	高频头	行输出	开关变压器	CPU	其他
新红太阳	H1418K	TDQ-5B6-M	BSC60J	BCK-51	CHT0410-5P78	LA76810
新红太阳	H21K66	TDQ-5B6-M	BSC66J	BCK-51	CHT0410-5P78	LA76810
新红太阳	H21K55	TDQ-5B6-M	BSC66J	BCK-51	CHT0410-5P78	LA76810
新红太阳	H21K59(B)	TDQ-5B6-M	BSC60F	BCK-45	CHT0827	TB1238
新红太阳	H21K69	TDQ-5B6-M	BSC66J	BCK-51	CHT0410-5P78	LA76810
新红太阳	H2199KB(A)	TDQ-5B6-M	BSC66J	BCK-51	CHT0410-5P78	LA76810
新红太阳	H2183K	TDQ-5B6-M	BSC66J	BCK-51	CHT041?	LA76810
新红太阳	H2135K	TDQ-5B6-M	BSC66J	BCK-51	CHT0410-5P78	LA76810
新红太阳	H2151K	TDQ-5B6-M	BSC66J	BCK-24010L	CH04T1220	LA76818A
新红太阳	H2186W	TDQ-5B6-M	BSC66J	BCK-24014L	CH04T1220	LA76818A
新红太阳	H2188K	TDQ-5B6-M	BSC66J	BCK-51	CH04T1229	LA76810
新红太阳	H25S86(D)	TDQ-5B6-M	BSC68H	BCK-46D	CH12T1004	TDA8843
新红太阳	H2598K	TDQ-5B6-M	BSC73H	BCK-24901L	LC86F3345...	LA76832
新红太阳	H2551K	TDQ-3B9CF-1	?	BCK-24905L	CHT0410-5P78	LA76810
新红太阳	H2523K	TDQ-3B9CF-1	BSC69H	BCK-24901L	CHT0415	LA76810
新红太阳	H2511K	TDQ-3B9CF-1	BSC62J	BCK-24312L	CH04T1229	LA76832
新红太阳	H2583K	TDQ-3B9CF-1	BSC73H	BCK-24601L	LC86F3345...	LA76832
新红太阳	H2535K	TDQ-3B9CF-1	BSC73H	BCK-24601L	LC86F3345...	LA76832
新红太阳	H29S86	TDQ-5B6-M	?	BCK-24312L	CH05T1601	LA76832
新红太阳	H29D80E	TDQ-5B6-M	BSC62D	BCK-24208L	CH08T0607	LA76832
新红太阳	H2999KB	TDQ-3B9CF-1	BSC73H	BCK-24901L	LC86F3345...	LA76832,NJW1122
新红太阳	H34D80	TDQ-5B6-M	BSC70E4	BCK-46D	CH12T1004	TDA8843
新红太阳	H3489D	TDQ-5B6-M	BSC70E4	BCK-46D	CH12T1004	TDA8843
金太阳	G2136(K)	TDQ-5B6-M	BSC66J	BCK-51	CHT0410-5P78	LA76810,LA7840
金太阳	G2138(K)	TDQ-5B6-M	BSC66J	BCK-51	CHT0410-5P78	LA76810,LA7840
金太阳	G25D19	TDQ-5B6-M	BSC62E	BCK-46D	CHT1202	TDA8843,TDA8350,TDA7057AQ,HEF4053
金太阳	G25D19(B)	TDQ-5B6-M	BSC68F1	BCK-25403L	CHT0827	TB1238,TA8427
金太阳	G29D9(K)	TDQ-3B9CF-1	BSC68B	BCK-24901L	CHT0410-5P78	LA76810,LA7840
金太阳	G29D8	TDQ-5B6-M	BSC68H	BCK-46D	CHT1202	TDA8843,TDA8350,TDA7057AQ,HEF4053
金太阳	G29D8(K)	TDQ-3B9CF-1	BSC68H	BCK-24901L	CHT0410-5P78	LA76810,LA7840
金太阳	G2932(K)	TDQ-5B6-M	BSC68B	BCK-24901L	CHT0410-5P78	LA76810,LA7840
金太阳	G2936(K)	TDQ-5B6-M	BSC68B	BCK-24901L	CHT0410-5P78	LA76810,LA7840
金太阳	G3898(A)	TDQ-5B6-M	BSC70I	BCK-25423L	CHT1204	TDA8843,TDA9859,TDA8350Q,TDA7057AQ
CHD-5/5C	CHD2915	TDQ-6B7-FM2	BSC75M	BCK-25414L	MSP3413G	TA8256,LA7846,TDA6111Q,STR-6656,C5144,GZS10-301-2
CHD-5/6C	CHD2918	TDQ-6B7-FM2	BSC75M	BCK-25414L	MSP3413G	TA8256,LA7846,TDA6111Q,STR-6656,C5144,GZS10-301-2
CHD-5/7C	CHD2988	TDQ-6B7-FM2	BSC75M	BCK-25414L	MSP3413G	TA8256,LA7846,TDA6111Q,STR-6656,C5144,GZS10-301-2
CHD-5/8C	CHD2998/(A)	TDQ-6B7-FM2	BSC75M	BCK-25414L	MSP3413G	TA8256,LA7846,TDA6111Q,STR-6656,C5144,GZS10-301-2
CHD-5/9C	CHD2992/(A)	TDQ-6B7-FM2	BSC75M	BCK-25414L	MSP3413G	TA8256,LA7846,TDA6111Q,STR-6656,C5144,GZS10-301-2

机芯	代表机型	高频头	行输出	开关变压器	CPU	其他
CHD-5/10C	CHD2919	TDQ-6B7-FM2	BSC75M	BCK-25414L	MSP3413G	TA8256,LA7846,TDA6111Q,STR-6656,C5144,GZS10-301-2
CHD-5/11C	CHD2983	TDQ-6B7-FM2	BSC75M	BCK-25414L	MSP3413G	TA8256,LA7846,TDA6111Q,STR-6656,C5144,GZS10-301-2
CHD-5/12C	CHD3415/(A)	TDQ-6B7-FM2	BSC75C	BCK-25414L	MSP3413G	TA8256,LA7846,TDA6111Q,STR-6656,C5144,GZS10-301-2
CHD-5/13C	CHD3418	TDQ-6B7-FM2	BSC75C	BCK-25414L	MSP3413G	TA8256,LA7846,TDA6111Q,STR-6656,C5144,GZS10-301-2
CHD-5/14C	CHD3488	TDQ-6B7-FM2	BSC75C	BCK-25414L	MSP3413G	TA8256,LA7846,TDA6111Q,STR-6656,C5144,GZS10-301-2
CHD-5/15C	CHD3498/(A)	TDQ-6B7-FM2	BSC75C	BCK-25414L	MSP3413G	TA8256,LA7846,TDA6111Q,STR-6656,C5144,GZS10-301-2
CDT-1	CHD2990	TDQ6A7-FM2,TDQ-6A7-FM3W	BSC75A	BCK-25415L	MSP3413G	GZS10-2-AC3,TDA6111Q,HEF4053,C5144,BCT-7,NJW1147,LA7846
CDT-2	CHD2990(A)	TDQ6A7-FM2,TDQ-6A7-FM3W		BCK-25424L	MSP3413G	GZS10-2-AC3,TDA6111Q,HEF4053,C5144,BCT-7,NJW1147,LA7846
CDT-3	CHD2995	TDQ-6B1-MA	BSC75M3	BCK-25414L	TDA9370	
CDT-4	CHD3215	TDQ6A7-FM2,TDQ-6A7-FM3W	BSC75A	BCK-25425L	MSP3413G	GZS10-2-AC3,TDA6111Q,HEF4053,C5144,BCT-7,NJW1147,LA7846
CDT-5	CHD3490(A)	TDQ6A7-FM2,TDQ-6A7-FM3W	BSC75C	BCK-25424L	MSP3413G	GZS10-2-AC3,TDA6111Q,HEF4053,C5144,BCT-7,NJW1147,LA7846
CDT-6	CHD3495	TDQ-6B1-MA	BSC75G	BCK-25414L	TDA9370	
CDT-7	CHD3615	TDQ6A7-FM2,TDQ-6A7-FM3W	BSC75A	BCK-25415L	MSP3413G	GZS10-2-AC3,TDA6111Q,HEF4053,C5144,BCT-7,NJW1147,LA7846
CHD-7	CHD2918(T)	TDQ-6B1-MA	BSC75M3	BCK-25414L	TDA9370	GS10-2-AC3,C5144,STR-F6656
CHD-8	CHD3418(T)	TDQ-6B1-MA	BSC75M3	BCK-25414L	TDA9370	C5144,STR-F6656,GZS10-301-2,M52472,NJW1147,HEF4052
CHD-9	CHD3418S(T)	TDQ-6B1-MA	BSC75L	BCK-25414L	TDA9370	C5144,STR-F6656,GZS10-301-2,M52472,NJW1147,HEF4052
精显补充	DP2998W	TDQ-6A/B7-FM2	BSC75M	BCK-26415L	MSP3413G	STR-F6656
金锐	PF2118E	TDQ-5B6-M	BSC62V1	BCK-24009	CH08T0604	NJW1137,TDA8944,GZS10-2-108
金锐	PF2183	TDQ-5B6-M	BSC60K	BCK-51	CH05T1602	TDA8943,D1651
金锐	PF2155	TDQ-5B6-M	BSC60K	BCK-24326L	CH05T1609	3DD2102
金锐	PF2515(A)	TDQ-5B6-M	BSC68Z	BCK-24312L	CH05T1606	BU2720,STR-F6454
金锐	PF2539	TDQ-5B6-M	BSC68Z	BCK-24312L	CH05T1606	TDA8350,TDA7057AQ
金锐	PF2591E	TDQ-5B6-M	BSC62D	BCK-24208L	TMP8829	TDA8944
金锐	PF2599	TDQ-5B6-M	BSC62A	BCK-24312L	CH05T1606	GZS10-2-108
金锐	PF2588	TDQ-5B6-M	BSC68Z	BCK-24312L	CH05T1606	TDQ-7057AQ
金锐	PF2915	TDQ-5B6-M	BSC73K	BCK-24312L	CH05T1606	TDQ-7057AQ
金锐	PF2939	TDQ-5B6-M	BSC73K	BCK-24312L	CH05T1601	TDA9859,TDA7057AQ
金锐	PF2992	TDQ-5B6-M	BSC73K	BCK-24312L	CH05T1608	24C08
金锐	PF2999	TDQ-5B6-M	BSC73K	BCK-24312L	CH05T1603	TDA9859,TDA7057AQ
金锐	PF3498	TDQ-5B6-M	BSC70J	BCK-60	CH05T1606	TDA9859,TDA7057AQ
银锐	SF2111	TDQ-5B6-M	BSC60K	BCK-24326L	CH05T1609	TDA8943,D1651
银锐	SF2119	TDQ-5B6-M	BSC60K	BCK-51	TDA9370	TDA8943,D1651
银锐	SF2166K	TDQ-5B6-M	BSC60J2	BCK-23508L	CH04T1301	AN5265,LA78040

机芯	代表机型	高频头	行输出	开关变压器	CPU	其他
银锐	SF2136	TDQ-5B6-M	BSC60K	BCK-51	TDA9370	TDA8943,D1651
银锐	SF2183	TDQ-5B6-M	BSC60K	BCK-51	CH05T1602	TDA8943,D1651
银锐	SF2186	TDQ-5B6-M	BSC60K	BCK-51	TDA9370	TDA8943,D1651
银锐	SF2198	TDQ-5B6-M	BSC60K	BCK-51	TDA9370	TDA8943,D1651
银锐	SF2519	TDQ-5B6-M	BSC62A	BCK-24312L	CH05T1608	TDA9859,TDA7057AQ
银锐	SF2539	TDQ-5B6-M	BSC62A	BCK-24312L	CH05T1606	TDA9859,TDA7057AQ
银锐	SF2539(A)	TDQ-5B6-M	BSC62A	BCK-24312L	CH05T1606	TDA9859,TDA7057AQ
银锐	SF2583	TDQ-5B6-M	BSC62A	BCK-24312L	CH05T1606	TDA9859,TDA7057AQ
银锐	SF2588	TDQ-5B6-M	BSC62A	BCK-24312L	CH05T1608	TDA9859,TDA7057AQ
银锐	SF2598	TDQ-5B6-M	BSC62A	BCK-24312L	CH05T1601	TDA9859,TDA7057AQ
银锐	SF2599	TDQ-5B6-M	BSC62A	BCK-24312L	CH05T1603	TDA7057AQ,HEF4052
银锐	SF2911	TDQ-5B6-M	BSC70K	BCK-24312L	CH05T1608	TDA9859,TDA7057AQ
银锐	SF2911F	TDQ-5B6-M	BSC70K	BCK-24312L	CH05T1608	TDA9859,TDA7057AQ
银锐	SF2915	TDQ-5B6-M	BSC68Z	BCK-24312L	CH05T1601	TDA9859,TDA7057AQ
银锐	SF3939	TDQ-5B6-M	BSC68Z	BCK-24312L	CH05T1606	TDA9859,TDA7057AQ
银锐	SF2983	TDQ-5B6-M	BSC68Z	BCK-24312L	CH05T1603	TDA9859,TDA7057AQ
银锐	SF3415	TDQ-5B6-M	BSC70K	BCK-60	CH05T1601	TDA9859,TDA7057AQ
银锐	SF3411	TDQ-5B6-M	BSC70K	BCK-24312L	CH05T1608	TDA9859,TDA7057AQ
银锐	SF3411F	TDQ-5B6-M	BSC70K	BCK-24312L	CH05T1608	TDA9859,TDA7057AQ
银锐	SF3498	TDQ-5B6-M	BSC70K	BCK-24312L	CH05T1608	TDA9859,TDA7057AQ
银锐	SF2118E	TDQ-5B6-M	BSC60J	BCK-24009	CH08T0604	TDA8944J
银锐	SF2118E(M)	TDQ-5B6-M	BSC60J	BCK-24009	CH08T0611	TDA7055
银锐	SF2170E	TDQ-5B6-M	BSC60J	BCK-23604L	TMPA8803	TDA8943,D1651
银锐	SF2191E(G)	TDQ-5B6-M	BSC60J	BCK-24009	CH08T0609	TDA7055
银锐	SF2591E(G)	TDQ-5B6-M	BSC62D	BCK-24208L	TMP8829	TDA8944J
银锐	SF2518E	TDQ-5B6-M	BSC62D	BCK-24208L	TMP8829	TDA8944J
银锐	SF2566E	TDQ-5B6-M	BSC62D	BCK-24208L	CH08T0607	TDA8944AJ
银锐	SF2970E	TDQ-5B6-M	BSC62D	BCK-24208L	TMP8809	TDA8944J
银锐	SF2991E	TDQ-5B6-M	BSC62D	BCK-24208L	TMP8829	TDA8944J
银锐	SF3466E	TDQ-5B6-M	BSC70X1	BCK-24208L	CH08T0607	TDA8944J
银锐	SF3418EF	TDQ-5B6-M	BSC70X1	BCK-24913L	TMP8829	TDA8944J
银锐	H34D80E	TDQ-5B6-M	BSC70X1	BCK-24208L	CH08T0607	TDA8944J
精彩	PF2918E	TDQ-5B6-M	BSC70X	BCK-24913L	TMP8829	TDA8944J
精彩	PF3418E	TDQ-5B6-M	BSC70X	BCK-24913L	TMP8829	TDA8944J
精音	PF2193E	TDQ-5B6-M	BSC62V1	BCK-24009	CH08T0604	TDA8944J,TA1343N
精音	PF2993E	TDQ-5B6-M	BSC69C	BCK-24208L	TMP8807	TDA8944J,TA1343N
精艺	PF2195	TDQ-5B6-M	BSC60K	BCK-24306L	CH05T1609	TDA8943,D1651
精艺	PF2595	TDQ-5B6-M	BSC69A	BCK-24340L	CH05T1611	TDA8944J
精艺	PF2995	TDQ-5B6-M	BSC73K	BCK-24340L	CH05T1611	TDA8944J

机芯	代表机型	高频头	行输出	开关变压器	CPU	其他
精艺	PF3495	TDQ-5B6-M	BSC70J	BCK-24340L	CH05T1611	TDA8944J
二合一	PF1517DV	TDQ-5B6-M	BSC60W	BCK-24341L	TDA9370	TDA7057AQ,HEF4052
二合一	PF1581DV	TDQ-5B6-M	BSC60W	BCK-24341L	TDA9370	TDA7057AQ,HEF4052
二合一	PF2117DV	TDQ-5B6-M	BSC60K	BCK-24342L	TDA9370	TDA7057AQ,HEF4052
二合一	PF2181DV	TDQ-5B6-M	BCK60K	BCK-24342L	TDA9370	TDA7057AQ,HEF4052
二合一	PF2581DV	TDQ-5B6-M	BSC70V	BCK24211L	TDA937X	TDA8944J,TA1343N,TDA6108,TA1219
二合一	PF2917DV	TDQ-5B6-M	BSC73L	BCK24211L	TDA937X	TDA8944J,TA1343N,TDA6108,TA1219
二合一	PF2981DV	TDQ-5B6-M	BSC73L	BCK24211L	TDA937X	TDA8944J,TA1343N,TDA6108,TA1219
丽音	PF2118E(N)	TDQ-5B6-M	BSC62V1	BCK-24009	TMPA8801PS	NJW1137,TDA8944J,
锐弛	PF2123K	TDQ-5B6-M	BSC66J	BCK-24321L	CHT0410-5P78	LA76810
锐弛	PF2188K	TDQ-5B6-M	BSC66J	BCK-61	CH04T1229	LA76810
锐弛	PF2583K	TDQ-5B6-M	BSC60J	BCK-24312L	CH04T1229	LA76832,TDA7057AQ,6656
锐弛	PF2589D	TDQ-5B6-M	BSC62E	BCK25405L	CH12T1004	TDA8843/OM8839
锐弛	PF2599K	TDQ-5B6-M	BSC73S	BCK-24901L	LC86F3345...	LA76832,TDA7057AQ,6656
锐弛	PF2999D	TDQ-5B6-M	BSC73H	BCK-24311L	CH12T1004	TDA8843
锐弛	PF2989D	TDQ-5B6-M	BSC73H	BCK-46D	CH12T1004	TDA8843/OM8839
锐弛	PF34G8	MVCS43C,EC927L1	BSC70A	TPW-24312AE	TMP87CS38N	TA1222N,HIC1015, PIP, MPX
PDT-3	HP4368/5168/4388/5188/4888A/6188/W6588/7088/4390/5190	TDQ-6A7-FM1			CPU板,	DEA133B1,TDA9111,SID2500,2SC1815LM1876,
PDT-4	HP5189/5629/4388A/5188A/4390A/5190A/3891A/4391A/JP5625/5185	TDQ-6A7-FM1			CPU板,	DEA133B1,TDA9111,SID2500,2SC1815LM1876,
PDT-5	PDT-3			BCK-24317L,		
PDT-6	PDT-3				东芝CPU-TMP93CS45, W27040	
					三星CPU-KS88C4504,	