

创维液晶电视电源板代用表 更多彩电维修资料，请到彩电维修资料网 (<http://www.tv160.net>) 查询吧！

序号	物料	名称	代用物料1	代用物料2	代用物料3	备注
1	168P-P24AQN-00	LCD-电源板24S20HR/8K21通用(通用168P-P24TTU-00)	168P-P24TTU-00			
2	168P-P24TTU-10	LCD-电源板24S16IW/8R07(板号5800-P24TTU-0100)	168P-P24TTU-00	168P-P24AQN-00		
3	168P-P26TLF-10	LCD-电源板 26S12HR/8K20/26L08HR/8K21/26L16SW/8R03通用(通用168P-P26TLF-00)(板号5800-P26TLF-0100)	168P-P26TLF-00			
4	168P-P26TQM-00	LCD-电源板 26L03HR/26L08HR/26L10HR/26L16SW/8K21/8M01/8R01/8R03/奇美屏(板号5800-P26TQM-0010)	168P-P26TQM-10	168P-P26TQM-30		
5	168P-P26TQM-10	LCD-电源板 26M10HR/26S12HR/26L03HR/26L28HR/26S15HM/26L16SW/8K20/8K21/8M20/8R03通用(带背光)(板号5800-P26TQM-0110)	168P-P26TQM-00			
6	168P-P32ALK-00	LCD-电源板32L01HM/8M19/LG屏(屏版本号LC320W)(板号5800-P32TLK-0030)	168P-P32ALK-10			
7	168P-P37ALK-00	LCD-电源板37L05HR/8M60/LG屏(板号5800-P32TLK-0030)	168P-P37ALK-01			
8	168P-P32TTS-21	LED-电源板32LED10/37LED10/8M81通用(板号5800-P32TTS-0010)	168P-P32TTS-30	168P-P32TTS-22	168P-P32TTS-20	
9	168P-P32TRF-01	LCD-电源板 32L01HM/32L01DZ/32K10RN/37K10RN/8M19/8M79/夏普屏(板号5800-P32TTU-0120)	168P-P32TTU-10	168P-P32TTU-20	168P-P32TTU-00	
10	168P-P32TTU-10	LCD-电源板 32M10RM/37M10RM/37L01/42L01/32L05/37L05/8K28/8M19/8M60通用(板号5800-P32TTU-0130)	168P-P32TTU-20	168P-P32TTU-00	168P-P32TRF-01	
11	168P-P32TTU-20	LCD-电源板 32S11HR/32S12HR/37S12HR/8K20/32L03RM/8M73/37L01SW/42L01SW/8R10通用(板号5800-P32TTU-0200)	168P-P32TTU-10	168P-P32TTU-00	168P-P32TRF-01	
12	168P-P37TTF-00	LCD-电源板37L05HR(板号5800-P37TTF-0000)	168P-P37TTF-10	168P-P37TTF-01		
13	168P-P37TTF-01	LCD-电源板32M11HM/37M11HM/42M11HF/8M20通用(板号5800-P37TTF-0010)	168P-P37TTF-10	168P-P37TTF-00		
14	168P-P37TTF-10	LCD-电源板37L05HR/8M60(板号5800-P37TTF-0020)	168P-P37TTF-00	168P-P37TTF-01		
15	168P-P40TOS-00	LCD-电源板37/40/42寸 /8DA2/8DA5/8DA6/8DD1/8G10/8G11/8G12/8G20/8G21/8G29/8M10/8M11/8M19/8R06/8R08/8TAG/8TTN/8TTR通用(板号5800-P40TOS-00)-停产	5300-0942T0-01			
16	168P-P37AWM-00	LCD-电源板37L05HR/8K29/8M60/创维屏(板号5800-P42TLQ-0000)	168P-P37AWM-01			
17	168P-P37AWM-01	LCD-电源板37M11HM/8M20/创维屏(板号5800-P42TLQ-0040)	168P-P37AWM-00			

彩电维修资料网
http://www.tv160.net

创维液晶电视电源板代用表 更多彩电维修资料，请到彩电视维修资料网 (<http://www.tv160.net>) 查询吧！

序号	物料	名称	代用物料1	代用物料2	代用物料3	备注
18	168P-P42TTS-05	LCD-电源板42M10RF/42L05HF/8K28/8M60通用(板号5800-P42TTS-0050/0060)	168P-P42TTS-10	168P-P42TTS-00		
19	168P-P42TTS-00	LCD-电源板42L02HA-C/42L05HA-C/8M69/8M71通用(板号5800-P42TTS-10)	168P-P42TTS-10	168P-P42TTS-05		
20	168P-P42TTS-10	LCD-电源板 37L01HM/37L02RM/37L03RM/42L01/42L02/42L03/42L06/42L28RM-F/8DA5/8G20/8G28/8G29/8M19/8K23/8M68/8M73通用(板号5800-P42TTS-10)	168P-P42TTS-00	168P-P42TTS-05		
21	168P-P42TTT-10	LED-电源板42LED10/47LED10/8K81(板号5800-P42TTT-0000)	168P-P42TTT-11			
22	168P-P42TTT-11	LED-电源板42LED10/8K81(板号5800-P42TTT-0100)	168P-P42TTT-10			
23	168P-P46TTS-10	LCD-电源板47L03RF/8M68/47L05HR/8M58通用(板号5800-P46TTS-0000)	168P-P46TTS-01	168P-P46TTS-00	168P-P46TTS-02	
24	168P-P46TTS-01	LCD-电源板47L02HA-C/47L05HA-C/55L09HA-C/8M69/8M71通用(板号5800-P46TTS-01)	168P-P46TTS-00	168P-P46TTS-02	168P-P46TTS-10	
25	168P-P46TTS-00	LCD-电源板47L20HF/47L20HW/47L08RT-F/47L18RM-F/8DA2/8DD1/8G20通用(板号5800-P46TTS-02)-停产	168P-P46TTS-01	168P-P46TTS-02	168P-P46TTS-10	
26	168P-P46TTS-02	LCD-电源板47LED09/47L06RF/47L28RM-F/47L02RF/55L05RF/47L01HF/47L05HF/47L03RF/8D18/8DA5/8G22/8G28/8G29/8K23/8M19/8M60/8M68通用(板号5800-P46TTS-02)	168P-P46TTS-01	168P-P46TTS-00	168P-P46TTS-10	
27	168P-P32TLF-10	LCD-电源板23/26/32/46/47寸 /8DA2/8DA6/8DA8/8DD1/8G10/8G20/8G28/8G29/8K22/8K23/8M10/8M19/8M73/8R06/8R08/8TAG/8TT6/8TTY通用(534L-0932TL-00)(板号5800-PLCD26-01)	5800-PLCD32-04	534L-0932TL-00	533Z-091203-00	5300-092400-00
28	168P-P24TTU-00	LCD-电源板24S20HR/8K21(通用168P-P24AQN-00)-淘汰	168P-P24AQN-00			
29	168P-P26TWU-01	LCD-电源板26寸/26LED10/8K81/创维	168P-P26TWU-10			
30	168P-P26TWU-10	LED-电源板24E60HR/26E60HR/8M49/创维屏	168P-P26TWU-01			
31	168P-P32ALK-10	LCD-电源板32寸/32L05HR/8K29/LG	168P-P32ALK-00			
32	168P-P32TTS-20	LCD-电源板32LED10/8M81/创维淘汰未生产过	168P-P32TTS-22	168P-P32TTS-30		
33	168P-P32TTS-22	LED-电源板32LED10/37LED10/8M81通用	168P-P32TTS-20	168P-P32TTS-30		
34	168P-P32TTS-30	LED-电源板32E80RA/8M86/32E80/37E80RA/8M87通用	168P-P32TTS-20	168P-P32TTS-22		
35	168P-P32TTU-00	LCD-电源板32寸	168P-P32TTU-10	168P-P32TTU-20	168P-P32TRF-01	
36	168P-P37ALK-01	LCD-电源板37"/37S12HR/8K20/乐轩	168P-P37ALK-00			
37	168P-P37BW0-00	LCD-电源小板 37L05HR/8K29/8M60/37M11HM/8M20/37L01SW/8R10通用	168P-P37DWC-01			
38	168P-P37DWC-00	LED-电源板37LED10/8M81驱动小板	168P-P37DWC-00			

彩电视维修资料网
http://www.tv160.net

创维液晶电视电源板代用表 更多彩电维修资料，请到彩电维修资料网（<http://www.tv160.net>）查询吧！

序号	物料	名称	代用物料1	代用物料2	代用物料3	备注
39	168P-P37DWC-01	LED-电源板32LED10/37LED10/8M81驱动小板	168P-P37DWC-02			
40	168P-P37DWC-02	LCD-电源板32LED10/8M81/创维	168P-P37DWC-01			
41	168P-P37TTK-01	LCD-电源板 37L02RM/37L01HM/37L16HC/37L98PW/8G29/8M19/8R08 通用	168P-P37T00-08			
42	168P-P42TTT-32	LED-电源板42E80RA/8M86/8M87	168P-P42TTT-40			
43	168P-P42TTT-40	LCD-电源板47E60HR/8R80/LG	168P-P42TTT-32			
44	168P-P55TQC-00	LED-电源板55LED10/8K81/奇美屏	168P-P55TQC-01	168P-P55TQC-02		
45	168P-P55TQC-01	LCD-电源板55E80RA/8M86/LG	168P-P55TQC-00	168P-P55TQC-02		
46	168P-P55TQC-02	LED-电源板55E60HR/8R80/奇美屏	168P-P55TQC-00	168P-P55TQC-01		

注:1. 以上数据来自培训车间的日常维修报表。

2. 按照以上内容做代换的同时可能整机的功率会发生变化，务必事先跟用户做好解释工作。

3. 板卡申领建议：在可代用的情况下请以自产电源为首选。（订做比较容易）

4. 请结合物资管理科即时库存进行备料。

