

菜单	项目	说明	8844机芯											
			HP-2990	HP-2995	29F66	29F98	HP-3408	HP-3458D	HP-3499	34P5A-P	HP-3408D	29T6A-P	29F1A-P	34T2A-P
1.	AGC	AGC延迟调节	07	0B	08	0B	06	0B	0B	07	0B	0B	0B	0D
	VCO	中频设置	03	03	03	03	03	03	03	03	03	03	03	03
	YDL	Y延迟补偿	04	04	04	04	04	04	04	00	04	04	04	00
2	PSL/NSL	长斜度校正	16	1E	25	25	1D	1F	27	24	26	24	1E	21
	PVS/NVS	场中心	23	1B	1F	2B	25	24	25	23	1C	1B	1C	18
	PVA/NVA	场副	29	1C	21	2F	21	12	1A	10	0A	39	1E	23
	PHS/NHS	行中心	29	23	1C	28	24	23	25	28	22	27	25	22
	PEW/PEW	行幅	34	26	3A	3B	38	36	36	34	37	31	37	39
	PEP/NEP	枕校	22	1D	12	16	1F	17	1E	17	15	16	16	1E
	PEC/NEC	四角校正	20	0C	08	01	08	00	0D	09	00	11	0B	10
	PET/NET	梯形校正	1E	1D	24	20	1C	1D	22	21	22	10	1C	1D
	PSC/NSC	场S校正	03	08	0A	08	06	06	06	06	06	08	10	06
3	RG	红平衡	1F	19	24	1B	1D	1F	21	20	1E	1C	1E	20
	GG	绿平衡	22	20	1B	26	1E	1A	1F	20	23	1A	1C	23
	BG	蓝平衡	24	20	24	24	22	24	22	20	27	22	24	22
	SBT	副亮度	38	38	36	36	34	38	3F	32	32	38	30	32
	SCT	副对比度	3F	3F	36	36	32	3F	3F	3F	3F	3F	38	3F
	SCR	副色度	32	32	32	32	32	38	32	32	32	38	32	32
	STT	N制副色调	3F	3F	3F	3F	3F	3F	3F	3F	3F	3F	3F	3F
	CDL	阴极驱动电平	04	05	00	00	04	03	04	04	07	05	05	04
4	MV-R	电影模式-R提升	07	07	07	07	07	07	07	07	07	07	07	07
	NT-G	自然模式-G提升	07	07	07	07	07	07	07	07	07	07	07	07
	DY-B	动态模式-B提升	07	07	07	07	07	07	07	07	07	07	07	07
	SDTB	标准模式高音	32	32	32	32	32	32	32	32	32	32	32	32
	SDBS	标准模式低音	32	32	32	32	20	32	20	20	20	28	32	20
	SDBT	标准模式亮度	34	36	32	32	40	38	40	38	3B	36	32	38
	SDCT	标准模式对比度	38	40	50	50	50	50	50	50	50	50	50	50
	SDCR	标准模式色度	38	38	40	40	40	40	40	40	40	38	40	40
	SDSP	标准模式锐度	32	32	32	32	32	32	32	32	32	32	32	32
	SDTT	标准模式色调	32	32	32	32	32	32	32	32	32	32	32	32
5	BT1	图象增强选项1	0F	0F	00	00	00	00	00	00	0D	0D	00	00
	BT2	图象增强选项2	00	00	0F	0F	0F	0F	0F	0F	00	00	0F	0F
	ABS	黑电平延伸	30	10	30	30	10	10	10	10	10	10	30	10
	NLA	非线性放大	10	10	10	10	10	10	10	10	10	10	10	10
	VGM	伽玛校正	10	20	10	10	20	20	20	20	20	20	10	20
	PAK	峰值幅度调整	30	20	30	30	20	20	20	20	20	20	30	20
	STP	前后沿调整	30	30	30	30	30	30	30	30	30	30	30	30
	COR	降噪调节	10	30	10	10	30	30	30	30	30	30	10	30
	LWD	线宽控制	10	12	10	10	12	12	12	12	12	12	10	12
	YDL	Y延迟调节	04	03	04	04	03	03	03	03	00	03	04	03
6	OPTION1	功能选项1	05	02	3F	3F	1F	1F	3F	3E	02	02	1A	3E
	OPTION2	功能选项2	0F	07	0F	07	0F	0F	07	07	0F	07	07	07
	ROWCON	屏显上下位置	06	06	07	07	06	06	06	06	06	06	06	06
	CLMCON	屏显左右位置	0B	05	05	06	02	04	04	04	03	03	05	04
	OPTION3	功能选项3	00	14	80	80	80	80	80	84	84	94	04	84

[illegible]

[illegible]